

# PROBOX

## VOLTAGE PROTECTOR



15A

6A



## Technical Details

YOU BUY, WE PROTECT..

Brand	PROBOX
Manufacturer	FUELBOX, PLOT NO.32, CTS NO.11491, ROJA BAUGH, AURANGABAD, MAHARASHTRA, 431001.
Model	PROBOX 1006/PROBOX 1015
Product Dimension	7.3 x 5.5 x 5.8 cm/7.3 x 5.5 x 6.8 cm
Operating Range	90 to 320 VAC (50 hz)
Protection Range	165 to 270 VAC (+/- 5 V)
Maximum Load Current	6/15 Amp
Response Time	<40 msec
Enclosure Material	Polycarbonate
Compatible Device	Refrigerator, Air condition, TV, Washing Machine, Microwave Oven, Computer, Water Purifier etc.
Special Features	Adjustable Smart Delay, Fuse Protection
Country of Origin	INDIA
Item Weight	102gram

## Features

- Protects Appliances from High/Low Voltages and Surge (Operating Range from 165 VAC to 270 VAC)
- Auto and instant HIGH/LOW voltage cut off & restart
- Adjustable Smart Delay
- Fuse Protection
- Very compact and elevated design to avoid adjacent switch overlap
- Prevent appliance failures and burn outs
- Surge protection up to 2.5KV

# Product Description

## Voltage Fluctuation Protection:

This plug is used to detect the voltage fluctuations that happen at home and further protect your appliances from being affected. It automatically detects safe voltage range and keeps your appliance running safely under the shield of Smart Plug.

## Easy to use at home

This product with surge protection is very easy to use at home. Simply insert the smart plug into a wall power socket. Plug in your appliance power pin into the Smart Plug. Turn on the power as usual. That's it.

## LED Indication:

- Green LED Blinking: Product is sensing Voltage before turning ON Load
- Green LED Solid: Load is ON in Safe Mode
- Red LED Blinking: Load is OFF and Product has detected high voltage i.e. >270 VAC
- Blue LED Blinking: Load is OFF and Product has detected low voltage i.e. <165 VAC
- Purple LED Blinking: Load is OFF and Product has detected Fuse failure, kindly replace Fuse.

## How does this plug work?

When the mains power supply fluctuates more than the permissible level (usually between 165 to 270V), the power to your appliance is disconnected automatically. It therefore protects the appliances from the harmful power variations before it reaches them. This device offers surge protection for up to 4000 volts.

## Adjustable Smart Delay

Adjustable delay gives flexibility to use the product for different appliances. Like refrigerator and Air condition needs 3 min delay before restarting it whereas TV only need 5 sec delay. Startup delay ensures proper power conditions before applying power to your appliance connected to Smart Plug.

## Fuse Protection:

Product is equipped with fuse protection. Kindly replace the fuse when blown of respective ratings only. In order to replace the fuse kindly remove black fuse holder and replace the fuse at the backside.

## Terms of warranty:

1. Two year warranty from date of purchase against any kind of manufacturing defect shall apply.
2. Warranty Starts from your date of purchase.
3. Manufacturer reserves the rights to repair or replace the device.
4. Any kind of warranty claim arising due to misuse, physical damage, unauthorized service attempts or fiddling would not be covered under warranty result in termination of warranty.
5. Warranty liability on seller is limited to a maximum amount of selling price of the product. No consequential and indirect compensation are payable by the seller under any condition.
6. Warranty offered is "Carry In Type Warranty" which means customer has to bring or send the product to our registered address at his/her own cost in case of any after sales service is needed. This also implies that all logistical costs including inward and outward logistics for availing service within warranty period or post warranty period, has to be borne by the customer.

## Legal Disclaimer:

1. Manufacturer takes no direct, indirect or any type of consequential liability of whatsoever nature under any condition, of customer's appliances functioning or malfunctioning of his/her appliance by or after buying this product.
2. Product has to be used in a specific way and for the specified purposes well specified. Any deviation/s in usage may cause malfunction in the product may lead to any kind of failures including but not limited to fire hazards and electric shock. If proved to be misused, this may lead to termination of warranty.
3. Transaction/s of Supply of products is subject to Aurangabad Jurisdiction only.
4. In case of any claim or dispute, the financial consideration shall not be over and above selling price of the product.
5. Product should not be used exceeding its technical and other general usage limits. Failures proving to be on this account are not covered under warranty.



- 📍 823 GAIBI NAGAR, BEHIND ANAND CINEMA, BHIWANDI – 421302, MAHARASHTRA, INDIA.
- ✉ [sales@fuelbox.in](mailto:sales@fuelbox.in), [www.fuelbox.in](http://www.fuelbox.in)
- ☎ +91-9145795876

**PROBOX**  
VOLTAGE PROTECTOR  
Manufactured By FuelBox  
[www.fuelbox.in](http://www.fuelbox.in)